HP Color LaserJet Pro MFP M277n



You'd never expect this much performance from such a small package. This loaded MFP and Original HP Toner cartridges with JetIntelligence combine to give you the tools you need to get the job done.













Accomplish more with the time you have

- Create the professional-quality colour documents your business depends on—right in the office.
- Choose the MFP that's the smallest in its class, and prints from sleep mode faster than comparable devices.
- Access time-saving apps from the 3-inch (7.6 cm) touchscreen, and scan directly to email and the cloud.²
- Easily print Microsoft® Word and PowerPoint® documents—now directly from your USB drive.6

Easy mobile printing options

• Easily print from a variety of smartphones and tablets—generally no setup or apps required.³

More pages, performance, and protection

- Get more pages than ever before—using Original HP High-Yield Colour Toner cartridges with JetIntelligence.⁵
- · Count on professional quality at high speeds—high-impact powerful toner works best with your HP printer.
- Get the authentic HP quality you paid for with anti-fraud technology.
- Print right away with preinstalled toner cartridges. Replace them with optional high-yield cartridges.⁷

Meet everyday IT challenges head-on

- Safeguard data and easily manage devices with a suite of essential security and management features.
- Easily set up, print, and share with built-in Ethernet networking.
- Increase security, restore control, and help avoid additional expenses—with HP JetAdvantage Private Print.⁴
- Protect your investment with HP Care Pack. Let our HP certified engineers resolve all your technical issues.⁸
- 1 Comparison based on manufacturers' published specifications (as of November 2014) and includes color laser multifunction printers (MFPs) with print speed between 11 and 20 pages per minute (ppm).
- Requires a wireless access point and an Internet connection to the printer. Services require registration. App availability varies by country, language, and agreements. For details, visit hpconnected.com
- Local printing requires mobile device and printer to be on the same wireless network or have a direct wireless connection. Wireless performance is dependent on physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to an HP Web-connected printer. App or software and HP ePrint account registration may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and availability in your area. See hp.com/go/mobileprinting for more details. Some features require purchase of optional module
- Available only in North America and select European countries. Feature is available at no charge and requires the MFP be connected to the Internet with web services enabled. For more information, see hpjetadvantage.com
- As compared with maximum-capacity cartridge yields for predecessor products. For details, see hp.com/go/learnaboutsupplies
 Microsoft and PowerPoint are U.S. registered trademarks of the Microsoft group of companies. Feature works with Microsoft Word and PowerPoint 2003 and later. Only Latin language fonts are supported.
- High-yield Original HP 201X LaserJet Toner cartridges not included; please purchase separately.
- 8 For more details on HP Care Pack, go to hp.com/go/cpc

Technical specifications

Functions	Print, copy, scan, fax
Print	
Duplex print options	Manual
Print speed ¹	Black (normal, A4): Up to 18 ppm; Black (normal, letter): Up to 19 ppm; Colour (normal, A4): Up to 18 ppm; Colour (normal, letter): Up to 19 ppm
First page out	Black (A4, ready): As fast as 11.5 sec; Colour (A4, ready): As fast as 13 sec
Print technology	Laser
Print cartridges number	4 (1 each black, cyan, magenta, yellow)
Standard print languages	HP PCL 6, HP PCL 5c, HP postscript level 3 emulation, PCLm, PDF, URF, Native Office
Printer management	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP We
	JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac); HP Device Toolbox
Scan	
Scan type/technology	Type: Flatbed, ADF; Technology: Contact Image Sensor (CIS)
Scan speed ⁶	Normal, A4: Up to 21 ppm (b&w), up to 14 ppm (colour)
Scan resolution	Enhanced: Up to 300 x 300 dpi (ADF); up to 1200 x 1200 dpi (Flatbed); Hardware/Optical: Up to 300 x 300 dpi (colour and
C	mono ADF); up to 300 x 300 dpi, 600 x 600 dpi, 1200 x 1200 dpi (Flatbed)
Scan size Scan input modes	Flatbed: 216 x 297 mm (8.5 x 11.7 in); ADF: 216 x 356 mm (8.5 x 14 in) Front-panel scan, copy, e-mail, fax, or file buttons; HP Scan software; and user application via TWAIN or WIA
	PDF, searchable PDF, JPG, RTF, TXT, BMP, PNG, TIFF
Scan file format Copy	PDF, Sedictidate PDF, JPG, KTF, TX1, BMF, MNG, TIFF
Copy speed ²	Black (normal, A4): Up to 18 cpm; Black (normal, letter): Up to 19 cpm;
copy speed	Colour (normal, A4): Up to 18 cpm; Colour (normal, letter): Up to 19 cpm
First copy out	Black (A4, ready): As fast as 13.5 sec; Colour (A4, ready): As fast as 16 sec
Copy resolution	Black (text & graphics): Up to 300 x 420 dpi; Colour (text & graphics): 300 x 420 dpi (Flatbed),
	300 x 360 dpi (ADF)
Max no of copies	Up to 99 copies
Copier resize	25 to 400%
Copier settings	Number of copies; Reduce/Enlarge; Lighter/Darker; Optimize; Paper; Multi-page copy; Collation; Tray Select; Two-Sided; Draft Mode; Image Adjustment; Set as New Defaults; Restore Defaults
Fax	Draft Prode, image Aujustitient, Det as New Detautts, Nestore Detautts
Fax speed	33.6 kbps (maximum), 14.4 kbps (default); 3 sec per page (letter)
Fax resolution	Black (best): Up to 300 x 3000 dpi; Black (standard): 203 x 96 dpi; Black & White (fine): 203 x 192 dpi;
. a. resource!!	Black & White (superfine): 300 x 300 dpi
Fax memory (A4/letter)	Up to 400 pages
Connectivity	
Standard connectivity	Hi-Speed USB 2.0 port; built-in Fast Ethernet 10/100/1000 Base-TX network port; Host USB
Mobile print capability ³	HP ePrint, Apple AirPrint™, Mopria-certified, Mobile Apps
Network ready	Standard built-in Ethernet
Network capabilities	Via built-in 10/100/1000 Base-TX Ethernet; Auto-crossover Ethernet; Authentication via 802.11x
Wireless capability	No
Memory	256 MB
Processor speed	800 MHz
Duty cycle	Up to 30,000 pages; Recommended monthly page volume: 4 250 to 2,500 pages
Paper handling	
Input	150-sheet input tray, multipurpose tray
Output	100-sheet output tray
Media type	Paper (brochure, inkjet, plain), photo paper (borderless, HP premium, panoramic, plus tab), envelopes, labels, cards (greeting,
	index), transparencies
Media weight	52 to 163 g/m² (Uncoated/Matte, recommended), up to 175 g/m² Postcards, 200 g/m² HP Matte; 60 to 163 g/m² (Coated/Glossy, recommended), up to 175 g/m² Postcards, 220 g/m² HP Glossy
Madia sizos sustam	
Media sizes custom Dimensions (W x D x H)	76.2 x 127 to 215.9 x 355.6 mm (3 x 5 to 5 x 14 in)
Weight	420 x 384 x 322 mm (16.5 x 15.1 x 12.7 in) 15.3 kg (33.7 lb)
Weight What's in the box	HP Color LaserJet Pro MFP M277n (B3Q10A); HP 201A Black Original LaserJet Cartridge (~1,500 yield) and Introductory HP LaserJe
what s in the box	Colour cartridges (~700 colour composite (C/Y/M) yield); Installation guide; Printer documentation and software on CD-ROM;
	Power cord; USB cable
Warranty features	One-year exchange warranty
Systems	
Compatible operating systems	Windows: Windows XP (SP3) 32-bit and 64-bit, Windows Win7 (Including Starter Edition 32-bit and 64-bit), Windows Vista
	Including Starter Edition 32-bit, Windows Vista 64-bit, Windows Win8 Basic 32-bit, Windows Win8 Pro 32-bit, Windows Win8 Enterprise 32-bit, Windows Win8 Enterprise N 32-bit, Windows Win8 Basic 64-bit, Windows Win8 Pro 64-bit, Windows Win8
	Enterprise 64-bit, Windows Win8 Enterprise N 64-bit, Windows Win8.1 64-bit; Mac: OS X 10.7 Lion, OS X 10.8 Mountain Lion,
	OS X 10.9 Mavericks; Mobile Operating Systems: iOS, Android, Windows 8 RT; Other: Debian (5.0, 5.0.1, 5.0.2, 5.0.3) (supported by the systems in the systems in the system of the systems
	by the automatic installer), Fedora (9, 9.0, 10, 10.0, 11.0, 11, 12, 12.0), HPUX 11 and Solaris 8/9, Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package), SUSE Linux (10.3, 11.0, 11, 11.1, 11.2), Ubuntu (8.04, 8.04.1, 8.04.
	8.10, 9.04, 9.10, 10.04)
Minimum system requirements	PC: Windows: Windows XP (SP3) 32-bit and 64-bit, Windows Win7 (Including Starter Edition 32-bit and 64-bit), Windows Vista
	Including Starter Edition 32-bit, Windows Vista 64-bit, Windows Win8 Basic 32-bit, Windows Win8 Pro 32-bit, Windows Win8 Enterprise 32-bit, Windows Win8 Enterprise N 32-bit, Windows Win8 Enterprise N 32-bit, Windows Win8 Pro 64-bit, Windows Win8
	Enterprise 64-bit, Windows Win8 Enterprise N 64-bit, Windows Win8.1 64-bit; Mobile Operating Systems: Android, Windows 8
	RT; Other: Debian (5.0, 5.0.1, 5.0.2, 5.0.3) (supported by the automatic installer), Fedora (9, 9.0, 10, 10.0, 11.0, 11, 12, 12.0),
	HPUX 11 and Solaris 8/9, Linux (9.4, 9.5), Red Hat Enterprise Linux 5.0 (supported with a pre-built package), SUSE Linux (10.3 11.0, 11, 11.1, 11.2), Ubuntu (8.04, 8.04.1, 8.04.2, 8.10, 9.04, 9.10, 10.04); CD-ROM or DVD drive, or Internet connection;
	Dedicated USB or network or Wireless connection; 200 MB available hard disk space; compatible hardware (For operating
	system hardware requirements see microsoft.com); Mac: Mac OS X 10.7 Lion, OS X 10.8 Mountain Lion, OS X 10.9 Mavericks; Mobile: iOS; Internet; Dedicated USB or network or Wireless connection; 1 GB available hard disk space
Fonts and Typefaces	Mobile: IDS; Internet; Dedicated USB or network or Wireless Connection; I GB available nard disk space 84 scalable TrueType fonts. Additional Font Solutions available at hp.com/go/laserjetfonts
Control panel	3.0-in intuitive touchscreen control panel with colour graphic display; 3 Buttons (Home, Help, Back)
	Power supply type: Internal (Built-in) power supply; Power supply required: 110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz (+/- 3 Hz); 220-volt input voltage: 220 to 240 VAC (+/- 10%), 50 Hz (+/- 3 Hz) (Not dual voltage, product
Power	
Power	varies by part number with # Option code identifier); Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready),
Power	varies by part number with # Option code identifier); Power consumption: ⁵ 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.97 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts
	varies by part number with # Option code identifier); Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.97 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts (Manual-Off) (Auto-Off/Manual-On), 0.1 watts (Manual-Off)
	varies by part number with # Option code identifier); Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.97 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts (Manual-Off) (Auto-Off/Manual-On), 0.1 watts (Manual-Off) Inbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Fax
	varies by part number with # Option code identifier); Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.97 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts (Manual-Off) [Inbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Fax HP Device Toolbox, HP Fax Print Driver, HP Fax Setup Wizard, HP Product Improvement Study, HP Scan, HP TWAIN & WIA Scan Drivers, Scan to e-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services
	varies by part number with # Option code identifier): Power consumption.* 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.37 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts (Auto-Off/Manual-Onf), 0.1 watts (Manual-Off) lnbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Fax HP Device Toolbox, HP Fax Print Driver, HP Fax Setup Wizard, HP Product Improvement Study, HP Scan, HP TWAIN & WIA Scan Drivers, Scan to e-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), NET 3.5 SP1 (only installed for older Windows operating systems that lack); hobox CD (Mac Partition):
Software included	varies by part number with #0 ption code identifier): Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.37 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts (Manual-Off) Inbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Faw HP Device Toolbox, HP Pax Print Driver, HP Pax Setup Wizard, HP Product Improvement Study, HP Sca, HP TWAIN & WIA Scan Drivers, Scan to e-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), NET 3.5 SP1 (only installed for older Windows operating systems that lack); Inbox CD (Mac Partition): Welcome Screen (Redirects users to fly.com), or OS App Source for HP Laser Jet Software)
Software included	varies by part number with # Option code identifier); Power consumption.* 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Sleep) and setts (Sleep), 1.73 watts (Sleep), 1.73 watts (Sleep), 1.73 watts (Sleep), 1.73 watts (He Auto-Off/Auto-On-Michaeo n.A.), 0.1 watts (Auto-Off/Manual-On), 0.1 watts (Manual-Off) Inbox CD (Windrows Partition): PH Installed/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Fax HP Device Toolbox, HP Fax Print Driver, HP Fax Setup Wizard, HP Product Improvement Study, HP Scan, HP TWAIN 8. WIA Scan Drivers, Scan to 6-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services Assist (HP Comnected), NET 3.5 SP1 (only installed for older Windows operating systems that lack); Inbox CD Maa Partition): Welcome Screen (Redirects users to h_ccm, or SA pps Source for HP Laserlet Software) Acoustic power emissions** 6.4 BIA (printing at 18 ppm); Acoustic power emissions (ready): Inaudible;
Software included Acoustics	varies by part number with # Option code identifier); Power consumption.* 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.37 watts (HP Auto-Off/Auto-On-Wake on LAN), 0.1 watts (Manual-Off) Inbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Fax HP Device Toolbox, HP Pax Print Driver, HP Fax Setup Wizard, HP Product Improvement Study, HP Scan, HP TWAIN & WIA Scan Drivers, Scan to e-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), NET 3.5 SP1 (only installed for older Windows operating systems that lack); Inbox CD (Mac Partition): Welcome Screen (Redirects users to fly.com), or OS App Source for HP Laser let Software)
Software included	varies by part number with # Option code identifier). Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Glue) angel Sleep), 0.37 watts (HP Auto-Off/Auto-On-Wake on LAN), 0.1 watts (Auto-Off/Manual-On), 0.1 watts (Manual-Off) watts (HP Auto-Off/Manual-On), 0.1 watts (Manual-Off) inbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Fax HP Device Toolbox, HP Fax Print Driver, HP Fax Setup Wizard, HP Product Improvement Study, HP Scan, HP TWAIN & WIA Scan Drivers, Scan to e-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), NET 3.5 SP1 (only installed for older Windows operating systems that lack); Inbox CD (Mac Partition): Welcome Screen (Redirects users to hp.com, or OS App Source for HP LaserJet Software) Acoustic power emissions 6.4 B/O, (printing at 18 ppm); Acoustic power emissions (ready): inaudible; Acoustic pressure emissions bystander (active, printling): 50 dB(A); Acoustic pressure emissions bystander (ready): inaudible (Poperating temperature range: 15 to 30° C (59 to 86° F); Recommended operating temperature: 15 to 30° C
Software included Acoustics	varies by part number with # Option code identifier). Power consumption: 365 watts (Print/Copy), 10.5 watts (Ready), 2.7 watts (Sleep), 1.73 watts (Blue Angel Sleep), 0.37 watts (HP Auto-Off/Auto-On - Wake on LAN), 0.1 watts (Auto-Off/Manual-On), 0.1 watts (Manual-Off) linbox CD (Windows Partition): HP Installer/Uninstaller, HP PCL 6 print driver, DXP (Device Experience), User Guide, HP Send Faw HP Device Toolbox, HP Pax Print Driver, HP Pax Setup Wizard, HP Droduct Improvement Study, HP Scan, HP TWAIN & WIA Scan Drivers, Scan to e-mail setup Wizard, Scan to Folder Setup Wizard, HP Update, Product Registration Assist, HP Web Services Assist (HP Connected), NET 3.5 SP1 (only installed for older Windows operating systems that lack): Inbox CD (Mac Partition): Welcome Screen (Redirects users to hyp.com, or OS App Source for HP Laserlet Software) Acoustic power emissions: 6.4 B(A) (printing at 18 ppm); Acoustic power emissions fready): Inaudible; Acoustic pressure emissions bystander (ready): Inaudible

- Recommended operating humidity range: 10 to 80% RH;

 Resurred using ISO/IEC 24734, excludes first set of test documents. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

 First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.

 Any require a firmware upgrade to be compatible, download at hp.com/go/support.

 Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.

 HP recommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.

 Acoustic values subject to change. For current information see hp.com/support. Configuration tested: M277dw model, simplex printing or copying, A4 paper at an average of 18 ppm.

 Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.

To learn more, visit hp.com

© Copyright 2015 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Microsoft and Windows are registered trademarks of Microsoft Corporation. AirPrint and the AirPrint logo are trademarks of Apple Inc., registered in the U.S. and other countries. Linux is a U.S. registered trademark of Linus Torvalds. UNIX is a registered trademark of The Open Group. NetWare® is a trademark of Novell, Inc.

Ordering information

Number B3Q10A	Description HP Color LaserJet Pro MFP M277n Printer		
Supplies			
Number	Description		
CF400A	HP 201A Black Original LaserJet Cartridge (~1,500 pages)		
CF401A	HP 201A Cyan Original LaserJet Cartridge (~1,400 pages)		
CF402A	HP 201A Yellow Original LaserJet Cartridge (~1,400 pages)		
CF403A	HP 201A Magenta Original LaserJet Cartridge (~1,400 pages)		
CF400X	HP 201X Black Original LaserJet Cartridge (~2,800 pages)		
CF401X	HP 201X Cyan Original LaserJet Cartridge (~2,300 pages)		
CF402X	HP 201X Yellow Original LaserJet Cartridge (~2,300 pages)		
CF403X	HP 201X Magenta Original LaserJet Cartridge (~2,300 pages)		

Accessories

Number	Description
C6520A	HP USB Cable 2.0 (a-b) 3 meter

HP Care Pack

Number	Description
UX435E	HP 3-year Next Business Day Exchange Color LaserJet
	MFP-M SVC
UX449E	HP 3-year Onsite Exchange Color LaserJet
	MFP-M SVC
UX444E	HP 3-year Pickup Return Color LaserJet MFP-M SVC
UX439E	HP 3-year Return Color LaserJet MFP-M SVC

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack go to hp.com/go/cpc

Supported paper

Contact HP via phone: Asia: 65 6253 8500

Solutions

For more solutions information, please visit $\underline{\text{hp.com/go/gsc}}$













