MFC-J5730DW



BUSINESS INKJET SERIES

Print | Copy | Scan | Fax

All-In-One Business Inkjet Printer The robust and easy to use All-In-One



Key Features:

Up to A3 Printing

Automatic 2-sided (duplex)print, copy, scan, fax

Fast print speeds of up to 22 PPM monochrome and 20 PPM colour*

500 sheet paper input | 50 sheet ADF | 100 sheet Multi-Purpose tray

9.3 cm Touchscreen LCD

Wired and wireless connectivity

In-box High-yield Cartridges

Easy to use, productive and robust, the MFC-J5730DW has been engineered to deliver dependable quality, meeting the needs of demanding office environments.

- New build design delivers a more robust and easy to operate device suited to a busy work environment
- A new and improved print head increases machine life and ensures exceptional durability

With advanced paper handling the MFC-J5730DW can handle a variety of media types whilst helping you to stay productive with fast print speeds and a first page print in just 6 seconds.

- Stay prepared with a 500-sheet capacity paper tray and a 100 sheet multipurpose tray for printing on a wide range of media
- Enjoy fast and hassle free scanning of multi-paged documents with the 50 sheet 2-sided (duplex) Automatic Document Feeder (ADF)
- · Reduce print costs and paper usage with automatic 2-sided (duplex) print

Create professional marketing materials and vivid office handouts that won't smudge or fade over time. Keep print costs and frequency of replacements down too with our optional super high-yield cartridges

- With a newly developed ink formula you can enjoy professional quality prints with sharp black text and vivid colour documents
- Save time and money with optional super high-yield cartridges that deliver yields up to 3,000 monochrome and 1,500 colour pages**

Connect seamlessly in the office and on the go with Wi-Fi Direct[™] for wireless printing from your smartphone, tablet, laptop or desktop, without the need for a router.

- Stay connected with smartphone, tablet, laptop and desktop compatibility
- With Wi-Fi Direct[™] you don't need a router to connect

Capture and digitise A4 paper documents directly from the A4 Automatic Document Feeder (ADF) for electronic storage and sharing on the go.

- Scan to popular cloud storage services directly from the large 9.3cm intuitive swipe touchscreen
- Capture and convert documents with ease with our exclusive Brother Cloud Apps

General

Technology	Inkjet
LCD Display	9.3cm colour touchscreen
Memory	265MB
Local Interface	Hi-Speed USB 2.0
Wired Network Interface	10Base-T/100Base-TX
Wireless Network Interface	802.11b/g/n (Infrastructure Mode)
Ink Gauge Indication	Ink levels are displayed on the LCD screen

Printer Driver

Colour Printer

Speed	22 PPM monochrome & 20 PPM colour based on ISO/IEC 24734
Speed (Fast Mode)	Up to 35 PPM monochrome & up to 27 PPM colour
Warm-up Time	0 seconds
Resolution	1,200 x 4,800dpi (horizontal x vertical)
2- Sided (duplex) Print	Yes
Droplet Size	4pl for Black 1.5pl for C, M, Y (Colours)
Colour Enhancement	Brother Image Enhancement allows the user to customise colour output
FPOT (First Print Out Time)	5.5 seconds for Monochrome 6 seconds for Colour

Mobile / Web Based Printing & Scanning

	<u> </u>
Brother iPrint&Scan (Android)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device
Brother iPrint&Scan (iPad / iPhone / iPod)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch.
Brother iPrint&Scan (Windows® Phone)	Print from and scan to a smart phone running the Windows [®] Phone Operating System
Brother Print&Scan (Windows® 8 & RT)	Print from and scan to a Windows® 8 or Windows RT Tablet
Google Cloud Print 2.0	Print most common file types from any Google Cloud Print enabled application
AirPrint	Print most common file types from any AirPrint enabled application
Mopria	Print most common file types from Mopria supported Android devices
Brother Print Service Plugin	Print directly from Apps on Android 5.0 or later
Evernote ^{™6}	Print from and scan to Evernote [™] without using a PC
Box ⁶	Print from and scan to Box without using a PC
Dropbox ⁶	Print from and scan to Dropbox without using a PC
Google Drive ^{™6}	Print from and scan to Google Drive [™] without using a PC
OneDrive ⁶	Print from and scan to $Microsoft^{\circledast}$ OneDrive without using a PC
Flickr ^{®6}	Print from and scan to Flickr [®] without using a PC
Facebook ^{®6}	Print from and scan to Facebook [®] without using a PC
Evernote ^{™6}	Print from and scan to Evernote [™] without using a PC
OneNote ⁶	Scan to Microsoft [®] OneNote without using a PC

Printer Functions

N-up Printing ³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Booklet Printing ⁴	Print documents in A5 booklet format using automatic or manual 2-sided print
Print Profiles ³	Store your favourite driver settings as profiles to easily recall them (great for saving time and for less technically adept users)
Print Archive ⁴	An electronic carbon copy feature that saves an electronic copy of all printed documents as a PDF file
Black and White Only Mode ¹⁰	If a colour ink runs out, continue your print job in Mono Mode.

Open Interface

Brother Solutions	Allows the use of 3 rd party solutions & apps to increase
Interface (BSI)	security & productivity

¹Approx declared yield value in accordance with ISO/IEC 24711 ²Calculated with 80g/m² paper ³Windows[®] & Mac[®] only ³Windows[®] only ³Optional free download from the Brother Solutions Centre <u>http://solutions.brother.com</u> ⁶Must be web connected ⁷Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements ⁸It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2 ⁹Requires Brother Software ¹⁰Black & White only mode will expire up to a number of prints and period of time. See Product FAQs at <u>http://solutions.brother.com</u> for details & instructions.

USB Host

Direct Print	Print directly from a USB flash memory drive. The supported file type is JPEG.
Direct Scan	Scan directly to a USB flash memory drive. The supported file formats include: PDF, PDF/A, JPEG, TIFF

Scan

Scanner Type	Dual CIS (Contact Image Sensor)
Colour & Monochrome Scanning	Yes
Scan Speed Monochrome	14 ipm (images per minute)
Single Pass 2-sided (duplex) Scan Speed Monochrome	10 ipm (images per minute)
Scan Speed Colour	14 ipm (images per minute)
Single Pass 2-sided (duplex) Scan Speed Colour	10 ipm (images per minute)
Scan Resolution from ADF	Up to 600 x 600dpi
Scan Resolution from Scanner Glass	Up to 1,200 x 2,400dpi
Interpolated Scan Resolution	Up to 19,200 x 19,200dpi
Colour Depth	16, 777, 216 colour variations (24 bit)
Grey Scale	256 shades of grey (8 bit)
Standard Functions ⁹	Scan to USB, E-mail, OCR, Image & File
Network Scanning	Scan to network folder (Windows [®] only), FTP, FTP over SSL, Email Server ^{5,} SharePoint ⁹ & Easy Scan to Email ⁶
Cloud Scanning ⁶	Scan direct to Evernote [™] , Box, Dropbox, Google Drive [™] , OneDrive, Flickr, Facebook, Evernote [™] , OneNote
Scan Features ⁹	Remove Background, Skip Blank Page, ID Scan, 1 to 2 Scan, Auto Deskew from ADF, Split PDF
Scan to Microsoft Office ⁶	Scan to Microsoft [®] Word, Microsoft [®] Excel & Microsoft [®] PowerPoint
Scan to Searchable PDF	Scan documents to searchable PDF files
Scan to SharePoint	Scan documents directly into SharePoint from Brother Control Centre 4 program
Outline & Scan ⁶	Draw around items to either scan a section or remove a section from the original document
Windows® Web Services Scanning	Scan direct into Windows® (from Windows® 7 & onwards) without needing to install a scanner driver
Left Document Notification	On screen and sound notification when a Document has been left on the Flatbed Scanner.

Scanner Driver

Windows®	TWAIN, WIA Windows® 10 (32 & 64 bit editions), Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions), Windows Vista® (32 & 64 bit editions),
Macintosh⁵	TWAIN & ICA v10.9.5/10.10.x/10.11.x
Linux⁵	SANE(32 & 64 bit editions)
Сору	
Speed – (A4) Monochrome/Colour	Up to 12/9cpm (copies per minute)
Automatic 2-Sided (duplex) Copying	Yes
FCOT (First Copy Out Time)	Less than 11 seconds from ready mode
Resolution	Up to 600 x 600 dpi
Multi-Copying / Stack / Sort	Makes up to 99 copies of each page / Stacks or Sorts
Enlargement / Reduction Ratio	Reduce or Increase document sizes from 25% to 400% in 1% increments
N in 1 Copying	Allows the user to compress 2 or 4 pages on to a single A4 sheet
2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet
Grey Scale	256 shades of grey (8 bit)
Outline & Copy ⁶	Draw around items to either copy a section or remove a section from the original document
Enlarge Text Copy ⁶	Makes reading copied documents easier if the size of the text on the original document is small

Address Book⁵

Speed Dials	100 x2 locations for E-mail addresses
Group Dial	A combination of up to 6 groups can be stored for broadcasting
LDAP	The ability to connect to an external LDAP enabled address book, like Microsoft [®] Exchange
Address books are only accessible	as part of the scan to email server function, available as an

optional free download from the Brother Solutions Centre http://solutions.brother.com

¹Approx declared yield value in accordance with ISO/IEC 24711 ²Calculated with 80q/m² paper ³Windows[®] & Mac[®] only ⁴Windows[®] only ⁵Optional free download from the Brother Solutions Centre <u>http://solutions.brother.com</u> ⁶Must be web connected ⁷Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer ⁸With a duty cycle that far exceeds your print requirements ⁸It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2 ⁹Requires Brother Software

Specifications are subject to change without notice.

Fax	
Fax Modem	33,600bps (Super G3)
Automatic 2-Sided (duplex) Faxing	Yes
Internet Fax (iFax)⁵	Fax documents anywhere in the world over the Internet without the use of a telephone line
PC Fax Send ^{9&3}	Send faxes directly from your PC
PC Fax Receive9&4	Receive faxes directly to your PC
Automatic Redial	Automatic redialling if the recipient fax is busy
Telephone Index	An electronic, alphabetical listing of stored speed dials and group numbers
Distinctive Ring Detection	An external service that allows two or more telephone numbers shared on a single fixed line and use different ring tones
Speaker / Ring volume	3 levels and off
Fax / Tel Switch	Automatic recognition of fax and telephone reception
Super Fine	Enables quality transmission of very small print and line drawings
Contrast	Auto / light / dark
Enhanced Remote Activate	Transfer a fax call, answered on an extension phone, to the fax machine
Delayed Timer	Up to 50
Quick-Scan	Reduce scanning times by scanning a fax into memory before sending. Approximately 2.5 seconds per page A4 standard resolution
Memory Transmission	Up to 200 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Out of Paper Reception	up to 200 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Dual Access	Allows the operator to perform 2 different tasks on the machine at the same time
Broadcasting	Send the same fax message to up to 50 separate locations
Batch Transmission	Stores documents for the same location in the machines memory for transmission in a single call
Auto Reduction	When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
ECM (Error Correction Mode)	The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Fax Forwarding	Sends a fax received in memory to another pre- programmed fax number
Remote Access	Allows users to remotely access their machine
Fax Retrieval	Allows remote access to faxes stored in the machine
Remote Set-up ³	Allows users to set-up the MFC from their PC
Grey Scale	256 shades (8 bit) of grey are available for faxing
Fax Preview	Preview received faxes on the screen
Fax stamp	Add the date and time to all received faxes
rax stamp	

Standard Paper Handling

Paper Input ²	Standard Tray – 250 sheets
	Lower Tray – 250 sheets
	Multi Purpose Tray – 100 sheets
	Automatic Document Feeder (ADF) – 50 sheets
Paper Output ²	Face up - 100 sheets

Media Specification

incula specification	
Media Types & Weights ⁸	Standard Tray – Plain, Inkjet, Glossy* & Recycled paper (between 64 - 220g/m ² , 260/m ² when using Brother BP-71 Glossy Paper) *Glossy up to A4 only Lower Tray – Plain & Recycled (between 64 - 120g/m ²) Multi Purpose Tray - Plain, Inkjet, Glossy* & Recycled paper (between 64 - 220g/m ² , 260/m ² when using Brother BP-71 Glossy Paper) *Glossy up to A3 Automatic Document Feeder (ADF) – plain & recycled paper (between 64 - 90g/m ²) 2-sided Print - plain & recycled paper (between 60 - 120g/m ²)
Envelope Printing	Yes : Accuracy & reliability will depend on the quality & type of envelopes or labels used
Media Sizes	Standard Tray - A3, LGR, LGL, A4, LTR, EXE, Folio, A5, A6, Photo(10x15cm), Indexcard(13x20cm), Photo-L(9x13cm), Photo-2L(13x18cm), Com-10, DL Envelope, Monarch, C5, Mexico Legal, India Legal Lower Tray - A4, LTR, A3, LGR, LGL, Folio, Mexico Legal, India Legal Multi Purpose Tray-A3, LGR, LGL, A4, LTR, EXE, Folio, A5, A6, Photo(10x15cm), Indexcard(13x20cm), Photo-L(9x13cm), Photo- 2L(13x18cm), C5, Com-10, DL Envelope, Monarch, Mexico Legal, India Legal 2-sided (duplex) Print – PC Print: A4, LTR, EXE, A5 Copy: A4, LTR, A5 Automatic Document Feeder (ADF) - Width: 105mm to 215.9mm x Length: 148mm to 355.6mm Scanner Glass -Up to Width: 215.9mm x Length: 297mm

Supplies

The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, and the type of media.

¹Approx declared yield value in accordance with ISO/IEC 24711 ²Calculated with 80q/m² paper ³Windows[®] & Mac[®] only ⁴Windows[®] only ⁵Optional free download from the Brother Solutions Centre <u>http://solutions.brother.com</u> ⁶Must be web connected ⁷Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer ⁸With a duty cycle that far exceeds your print requirements ⁸It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2 ⁹Requires Brother Software

Specifications are subject to change without notice.

Network & Security

Wired Network Built in Ethernet 10Base-T/100Base-TX Wireless Network IEEE 802.11b/g/n (Infrastructure Mode) Wi-Fi Direct [™] Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported) Wireless Setup Support Wi-Fi Protected Setup (WPS) Network Protocols TCP/IP (IPv4 and IPv6) IPv4 ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client, FTP Server, SIMPV/Jv2c/v3, TTFP server, SIMPV Client, SNTP Client, POP3, LDAP, INAP4, HTTP Server IPv4 FTP/FTPS Client FTP Server, SIMPVJ/v2c/v3, TTFP server, WOP3 & IMAP4 active only when Scan to Email Server is downloaded IPv6 (off by default) NDP, RA, mDNS, LLMNR Responder, DNS Resolver, IPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client FTP, SIMPVJ/v2c/v3, TTFP server, "POP3 & IMAP4 active only when Scan to Email Server is downloaded Wired Network Security 802 1x (EAP-MDS, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos "When Internet FAX is downloaded. Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Werberos, IPSec, 802.1x (LEAP-FAST, PEAP, EAP-TLS, EAP-TTLS), "When Internet FAX is downloaded. Wireless Certification WPA"/WPA2 ^M - Enterprise, Persona) , Wi-Fi Protected Setup (WPS) Wireless Certification WPA"/WPA2 ^M - Enterprise, Persona) , Wi-Fi Protected Setup (WPS) Subwen Internet FAX is downloaded. <th>Network & Security</th> <th></th>	Network & Security	
Wi-Fi Direct TM Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported) Wireless Setup Support Wi-Fi Protected Setup (WPS) Network Protocols TCP/IP (IPV4 and IPV6) ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBiOS name resolution, DDS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, ETP/FTPs Client FTP Server, SMIPV1/v2c/v3, TFTP server, SMIP Client, ICMP, Web Services (Print/Scan), CIFS Client, SINP Client, POP3, LDAP, IMAP4, HTTP Server IPv6 (off by default) NDP, RA, mDNS, LLMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, ETP/FTPS Client, FTP, SIMPV1/v2c/v3, TFTP server, SMIPC Client, SMTP Client, POP3, LDAP, IMAP4, ITTP Server IPv6 (off by default) NDP, RA, mDNS, LLMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, ETP/FTPS Client, FTP, SIMPV1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3, IAAP4, ICMPv6, HTTP Server Wired Network Security SMTP-AUTH, SSL/TLS (IPPS, HTTPS, FTPS, SMTF, POP3, IMAP4, SMIP4, SMIP v3 Wireless Network Security SMCP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTF, POP3, IMAP4*), SMIP4*, SMTPA, SMPA2-PSK (MS), SMTP AP3, SMIP4*, SMTPA, SMPA2-PSK (MS), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTF, POP3, IMAP4*), SMMP4*, SMPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTF, POP3, IMAP4*), SMTPA*, SMPA2-PSK (MS), SMTPA2*, POP3, IMAP4*), SMMP4*, SMPA2*, SMTP, AP-TLS, EAP-TTLS) Wireless Certification WPA*/WPA2** Enterprise, Persona) , Wi-Fi Protected Setup (WP5)	Wired Network	Built in Ethernet 10Base-T/100Base-TX
Wi-Fi Direct TM wireless access point (both automatic and manual methods supported) Wireless Setup Support Wi-Fi Protected Setup (WPS) Network Protocols TCP/IP (IPv4 and IPv6) IPv4 ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, TFP/FTPs Client, FTP Server, SNMP1/v2c/v3, TFTP server, SMTP Client, ICMP, Web Services (Print/Scan), CIFS Client, SNTP Client, POP3, LDAP, IMAP4, HTTP Server is downloaded IPv6 (off by default) NDP, RA, mDNS, LLMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client, FTP, SAMPV1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CISC Client, SNTP Client, PDP3*, CISC Client, SNTP Client, FDP3*, CISC Client, SNTP Client, PDP3*, ITP Server * 0OP3 & IMAP4 active only when Scan to Email Server is downloaded Wired Network Security 802.1x (CAP-MDS, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos * NMP-AUH, SSL/TLS (IPPS, HTTPS, STTP, S), Kerberos * NMP-AUH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, IAS, PAP-FST, TPAP, EAP-TLS, EAP-TTLS), Kerberos * NMR-APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, IAS, Is downloaded. Wireless Certification WPA*/WPA2* - Enterprise, Persona) , Wi-FI Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Notifications Receive usage reports on a regular basis via e-mail IP Filter	Wireless Network	IEEE 802.11b/g/n (Infrastructure Mode)
Network Protocols TCP/IP (IPV4 and IPV6) ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLIMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP Server; SMMPu1/v2c/v3, TFTP server; SMTP Client, ICMP, Web Services IPv4 FTP/FTPS Client FTP Server; SMMPu1/v2c/v3, TFTP server; SMTP Client, ICMP, Web Services PV63 IMAP4, HTTP Server *POP3 & IMAP4 active only when Scan to Email Server is downloaded IPv6 (off by default) NDP, RA, mDNS, LLIMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP , SMMPu1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CIFS Client, SNTP Client, LDAP, IMAP4*, ICMPv6, HTTP Server *POP3 & IMAP4 active only when Scan to Email Server is downloaded Wired Network Security SIMP-AUTH, SSL/TLS (IPPS, HTTPS, FTPS, SMTP, POP3*, IMAP4*), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos *When Internet FAX is downloaded. Wireless Network Security SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (IEAP, EAP-FAST, PEAP, EAP-TLS), EAP-TLS) Wireless Certification WPA**/WPA2** - Enterprise, Persona) , Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Reports Restrict which network users can or cannot access the device over the network (IPV4 only) Restrict Nich Ape-VA	Wi-Fi Direct [™]	wireless access point (both automatic and manual
IPv4 ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLIMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP Server; SNMPu1/v2c/v3, TFTP server; SMTP Client, ICMP, Web Services (Print/Scan), CIFS Client, SNTP Client, POP3, LDAP, IMAP4, HTTP Server IPv6 (off by default) NDP, RA, mDNS, LLIMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP , SMMPu1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CIFS Client, SNTP Client, IDAP, IMAP4*, ICMPv6, HTTP Server Wired Network Security SIMPA4 active only when Scan to Email Server is downloaded Wired Network Security SIMPA4 active only when Scan to Email Server is downloaded Wired Network Security SIMP-AUTH, SSL/TLS (IPPS, HTTPS, FTPS, SMTP, POP3*, IMAP4*), SNMP v3 Wireless Network Security S02.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos *When Internet FAX is downloaded. Wireless Certification WPA*/SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (EAP, EAP-FAST, PEAP, EAP-TLS), EAP-TLS) *When Internet FAX is downloaded. Wireless Certification WPA*/WPA2** - Enterprise, Persona) , Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Reports Restrict which network users can or annot access the device over the network (IPv4 only) Restrict brinting activity to individual or groups of Secure Function Lock	Wireless Setup Support	Wi-Fi Protected Setup (WPS)
WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP Server, SNMPv1/v2c/v3, TFTP server, SMTP Client, ICMP, Web Services (Print/Scan), CIFS Client, SNTP Client, POP3, LDAP, IMAP4, HTTP Server IPv6 (off by default) NDP, RA, mDNS, LLMNR Responder, DNS Resolver, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client FTP, SMMPv1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CIFS Client, SNTP Client, LDAP, IMAP4*, ICMPv6, HTTP Server Wired Network Security APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, FTPS, SMTP, POP3*, IMAP4*), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos *When Internet FAX is downloaded. Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos *When Internet FAX is downloaded. Wireless Network Security SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS) Wireless Certification WPA TM /WPA2 TM - Enterprise, Persona), Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Notifications Receive usage reports on a regular basis via e-mail P Filter Restrict which network users can or cannot access the device over the network (IP44 only) Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users <t< td=""><th>Network Protocols</th><td>TCP/IP (IPv4 and IPv6)</td></t<>	Network Protocols	TCP/IP (IPv4 and IPv6)
IPv6 (off by default) LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPS Client FTP, SNMPv1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CIFS Client, SNTP Client, LDAP, IMAP4*, ICMPv6, HTTP Server *POP3 & IMAP4 active only when Scan to Email Server is downloaded Wired Network Security APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, FTPS, SMTP, POP3*, IMAP4*), SMMP v3 Wireless Network Security 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos *When Internet FAX is downloaded. WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS) *Wireless Network Security SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS) *When Internet FAX is downloaded. Wireless Certification Wireless Certifications WPA™/WPA2™ - Enterprise, Persona) , Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Reports Receive usage reports on a regular basis via e-mail IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only) Receive usage reports on a segular basis via e-mail Restrict printing activity to individual or groups of users over a ne	IPv4	WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client FTP Server, SNMPv1/v2c/v3, TFTP server, SMTP Client, ICMP, Web Services (Print/Scan), CIFS Client, SNTP Client, POP3, LDAP, IMAP4, HTTP Server *POP3 & IMAP4 active only when Scan to Email
Wired Network Security SMTP, POP3*, IMAP4*), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), kerberos *When Internet FAX is downloaded. Wireless Network Security WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS) et When Internet FAX is downloaded. Wireless Certification WPA™/WPA2™ - Enterprise, Persona) , Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Reports Receive usage reports on a regular basis via e-mail IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only) Restrict parting activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users Active Directory N/A LDAP Authentication N/A	IPv6 (off by default)	LPR/LPD, Custom Raw Port/Port9100, IPP, FTP/FTPs Client FTP, SNMPv1/v2c/v3, TFTP server, Web Services (Print/Scan), SMTP Client, POP3*, CIFS Client, SNTP Client, LDAP, IMAP4*, ICMPv6, HTTP Server *POP3 & IMAP4 active only when Scan to Email
(AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, Wireless Network Security SMTP, POP3*, IMAP4*), SMMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS) *When Internet FAX is downloaded. Wireless Certification WPA™/WPA2™ - Enterprise, Persona), Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Reports Receive usage reports on a regular basis via e-mail IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only) Restrict printing activity to individual or groups of Secure Function Lock 3.0 users over a network. Can be used with PC User Login Name for up to 10 users Active Directory Authentication N/A LDAP Authentication N/A	Wired Network Security	SMTP, POP3*, IMAP4*), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP- TTLS), Kerberos
Wireless Certification Wi-Fi Protected Setup (WPS) Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing E-mail Reports Receive usage reports on a regular basis via e-mail IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only) Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users Active Directory N/A LDAP Authentication N/A	Wireless Network Security	(AES), APOP*, SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP3*, IMAP4*), SNMP v3, Kerberos, IPSec, 802.1x (LEAP, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS)
E-mail Notifications when it requires attention, such as when the toner is low or needs replacing E-mail Reports Receive usage reports on a regular basis via e-mail IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only) Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users Active Directory N/A LDAP Authentication N/A	Wireless Certification	
IP Filter Restrict which network users can or cannot access the device over the network (IPv4 only) Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users Active Directory N/A LDAP Authentication N/A Setting Lock N/A	E-mail Notifications	when it requires attention, such as when the toner
IP Filter the device over the network (IPv4 only) Restrict printing activity to individual or groups of users over a network. Can be used with PC User Login Name for up to 10 users Active Directory N/A LDAP Authentication N/A Setting Lock N/A	E-mail Reports	Receive usage reports on a regular basis via e-mail
Secure Function Lock 3.0 users over a network. Can be used with PC User Login Name for up to 10 users Active Directory Authentication LDAP Authentication N/A Setting Lock	IP Filter	
Authentication N/A LDAP Authentication N/A Setting Lock N/A	Secure Function Lock 3.0	Restrict printing activity to individual or groups of users over a network. Can be used with PC User
Setting Lock N/A	,	N/A
	LDAP Authentication	N/A
Secure Print ³ N/A	Setting Lock	N/A
	Secure Print ³	N/A

Fleet Management Tools

Unattended Installer ⁴	Ability to centrally deploy and customise our drivers and software
MSI Installer ⁴	Modular installers that can be distributed through Active Directory [®]
Embedded Web Server	Web based print management software embedded onto the device
	5 LAN/WAN management software
Driver Deployment Wizard	⁴ Easily create print drivers for hassle free deployment over your network

Environment

Power Consumption	Operating - 30W Ready - 6.5W
	Sleep - 1.6W
	Off - 0.04W
Sound Pressure Level	50dB(A) (Approx.)
Sound Power Level	Monochrome: 6.17B(A)
	Color: 6.13B(A)
Ink Save Mode	Yes
Energy Star	Yes

Dimensions & Weight

With Carton (WxDxH)	639 x 469 x 511mm 24.3KG
Without Carton (WxDxH)	530 x 398 x 374mm 20.6KG

Duty Cycles

Recommended Monthly 250 to 2000 pages, monthly print volume

¹Approx declared yield value in accordance with ISO/IEC 24711 ²Calculated with 80g/m² paper ³Windows⁸ & Mac[®] only ⁴Windows⁹ only ⁵Optional free download from the Brother Solutions Centre <u>http://solutions.brother.com</u> ⁶Must be web Cannected ⁸It is recommended to use the straight paper output path and the quiet mode feature with paper weights over 105g/m2 ⁹Requires Brother Software